

JD Plant Services Ltd

Battery charger information chart

Voltage	Amps	Vac input	Cabinet	8-9 Hr charge	12-13 Hr charge
24	10	230	P6	42-69	42-69
24	15	230	P6	96-110	70-83
24	20	230	P6	111-132	84-109
24	30	230	P6	166-198	138-165
24	40	230	P6	199-263	166-220
24	50	230	P6	264-329	221-275
24	60	230	P6	323-395	276-330
24	60	400	P6	323-395	276-330
24	80	230	P6	396-526	331-440
24	80	400	I2B	396-526	331-440
24	100	230	I2B	527-658	441-550
24	100	400	I2B	527-658	441-550
24	120	230	I2B	659-789	551-660
24	120	400	I2B	659-789	551-660
24	140	400	I2B	790-921	661-770
24	160	400	I2B	922-1052	771-880
24	180	400	I2B	1053-1184	881-990
36	20	230	P6	84-109	111-132
36	25	230	P6	110-137	133-165
36	30	230	P6	138-165	166-198
36	40	230	P6	166-220	199-263
36	50	230	P6	221-275	264-329
36	60	230	P6	276-330	323-395
36	60	400	I2B	276-330	323-395
36	80	230	I2B	331-440	396-526
36	80	400	I2B	331-440	396-526
36	100	230	I2B	441-550	527-658
36	100	400	I2B	441-550	527-658
36	120	230	I2B	551-660	659-789
36	120	400	I2B	551-660	659-789
36	140	400	I2B	661-770	790-921
36	160	400	I2B	771-880	922-1052
36	180	400	I2B	881-990	1053-1315
48	30	230	P6	138-165	166-198
48	40	230	P6	166-220	199-263
48	50	230	P6	221-275	264-329
48	60	230	P6	276-330	323-395

JD Plant Services Ltd

48	60	400	I2B	276-330	323-395
48	80	230	I2B	331-440	396-526
48	80	400	I2B	331-440	369-526
48	100	230	I2B	441-550	527-658
48	100	400	I2B	441-550	527-658
48	120	230	I2B	551-660	659-789
48	120	400	I2B	551-660	659-789
48	140	400	I2B	661-770	790-921
48	160	400	I2B	771-880	922-1052
48	180	400	I2B	881-990	1053-1184
72	60	230	I2B	276-330	323-395
72	60	400	I2B	276-330	323-395
72	80	230	I2B	331-440	396-526
72	80	400	I2B	331-440	396-526
72	100	230	I2B	441-550	527-658
72	100	400	I2B	441-550	527-658
72	120	230	I2B	551-660	659-789
72	120	400	I2B	551-660	659-789
72	140	400	I2B	661-770	790-921
80	60	230	I2B	221-330	323-395
80	60	400	I2B	221-330	323-395
80	80	230	I2B	331-440	396-526
80	80	400	I2B	331-440	396-526
80	100	230	I2B	441-550	527-658
80	100	400	I2B	441-550	527-658
80	120	230	I2B	551-660	659-789
80	120	400	I2B	551-660	659-789
80	140	400	I3	661-770	790-921
80	160	400	I3	771-880	922-1052
80	180	400	I3	881-990	1053-1184

Cabinet Type	Dimensions (mm)
P6	L 480 x D 280 x H 310
I2B	L 550 x D 450 x H 900
I3	L 700 x D 550 x H 1150

**Air pump chargers are available on request. Any further questions please do not hesitate to contact our sales team for further assistance on....
01752 205027 or email, nick@jdplantservices.co.uk**